



Installation of HELIAX® 4.3-10 Push-Pull Jumper Products

Bulletin 7818583 Revision L Page 1 of 2

1 Maintain 2-inch straight cable length behind the cable.

Do not hold the connector and bend the cable directly behind it, rather hold the cable adjacent to the connector to keep stress from the cable/connector junction.



2 Do not exceed the cable minimum bend radius.


Single Bend Radius Table*

Cable	Radius, inches
FSJ1	1.00 (25.4mm)
LSF2	1.00 (25.4mm)
FSJ4 / RSJ4	1.25 (31.8mm)
LDF 4	2.00 (51.0mm)
C141 / RG402	0.40 (10.0mm)

*Note: Requires use of mandrel to achieve single bend radius.

3 Route and form the cable in place prior to attach the coupling nuts.





4 Do not twist the cable into position.



5 Do not attach the connector coupling nut of one jumper connector and leave the opposite end hanging unattached.

6 Assemble: Hold the connector body and push it onto the female interface. Slightly rotate the coupling nut to ensure groove of coupling nut not align with the pins. (FSJ1 and LSF2 Push-Pull connector only) DO NOT hold the coupling nut while pushing on.

Disassemble: Slightly rotate the coupling nut to ensure groove of coupling nut align with the pins. (FSJ1 and LSF2 Push-Pull connector only) Hold the connector body stationary and pull back the coupling nut to disengage. DO NOT pull back the connector body.



Tip: Listen for a click sound to fully engage

Assemble: Rotate the coupling nut slightly to help a click sound for fully engaged.


Disassemble: Rotate the coupling nut slightly to help pull back.




Installation of HELIAX® 4.3-10 Push-Pull Jumper Products

Bulletin 7818583 Revision L Page 2 of 2

- 7** If cable jumper applying HELIAX® SureGuard Version 2.0 Weatherproofing boots, please refer to below.



- 8** For jumper didn't apply HELIAX SureGuard weatherproofing boots, recommend to seal with weatherproofing tape (ANDREW 221213 or equivalent) for outdoor applications.
If cable jumper applying weatherproofing tape, the manufacturer's recommendations are referenced below.



NOTE: Connector interface threads and O-rings are designed for mate ability without ANY supplementary treatment to threads or O-rings. If any type of supplementary lubricants/oils are used, the warranty will be void, and connector/assembly performance may be affected.



Scan For
Installation Video

ANDREW an Amphenol company

2601 Telecom Parkway, Richardson, Texas, 75082, USA
www.andrew.com

Technical Support

+1 888 297 6433, Option 3 (Toll Free US and Canada)
awpnarsupport@andrew.com

Notice: ANDREW disclaims any liability or responsibility for the results of improper or unsafe installation, inspection, maintenance, or removal practices.
Aviso: ANDREW no acepta ninguna obligación ni responsabilidad como resultado de prácticas incorrectas o peligrosas de instalación, inspección, mantenimiento o retiro.
Avis: ANDREW décline toute responsabilité pour les conséquences de procédures d'installation, d'inspection, d'entretien ou de retrait incorrectes ou dangereuses.
Hinweis: ANDREW lehnt jede Haftung oder Verantwortung für Schäden ab, die aufgrund unsachgemäßer Installation, Überprüfung, Wartung oder Demontage auftreten.
Atenção: A ANDREW abdica do direito de toda responsabilidade pelos resultados de práticas inadequadas e sem segurança de instalação, inspeção, manutenção ou remoção.
Avvertenza: ANDREW declina eventuali responsabilità derivanti dall'esecuzione di procedure di installazione, ispezione, manutenzione e smontaggio improprie o poco sicure.
注意: ANDREW 公司申明對於不恰當或不安全的安裝、檢驗、維修或拆卸操作所導致的後果不負責任 何義務和責任

©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners.

